

Ronin-SC Camera Compatibility List



2020.06.10 (for gimbal firmware v 1.5.0.40)

| Brand | Model | Cable | Control Features | Camera Setup Method | Power up the Camera (camera powered on) | Camera Firmware Version | |
|-----------|----------------|---|--|---|--|-------------------------|-------|
| | A9 | | | When using ① cable: 1. After connecting the cable, be sure to power on the Ronin-SC before the camera. Otherwise, the Ronin-SC will not recognize the camera. If the camera is not recognized, restart the camera or remove and reconnect the cable to the camera. 2. Optical zoom can be controlled through the Ronin-SC Focus Wheel (only lenses with built-in power zoom, such as the Sony E PZ 18-105 mm F4 G OSS). If a non-Power Zoom lens is mounted, the Focus Wheel will control digital zoom. Digital zoom must be enabled in your camera's settings. 3. After connecting with a Sony camera using the ① cable, if you need to swap to a camera of other manufacturers then a gimbal reboot is required. | | v3.10 | |
| | A6400 | ① Ronin-SC Multi-Camera Control Cable (Multi) (in the box) ② Ronin-SC Multi-Camera Control Cable (Type-C) (in the box) ③ Ronin-SC Multi-Camera Control Adapter (Type-C to Micro USB) (in the box) | When using ① cable: Capture photo Start/stop recording video Zoom control (digital or optical) Trigger auto focus When using ② + ③ cables: Start/stop recording video Pull focus electronically Trigger auto focus | When using ② + ③ cables: 1. Set the camera to MF mode. 2. Select "Network" and then turn off "Ctrl w/Smartphone". 3. Set the USB Connection to PC remote. 4. The Optical Image Stabilization of the camera will be disabled when using MCC-C cable, but OIS of the lens will not be affected. 5. When using the focus control electronically, if the lens has AF/MF modes, set it to AF mode, otherwise the electronic focus control function cannot be used. Note: When using the ② + ③ cable, the camera may not be able to use playback. In this case, put the gimbal in sleep mode. | When using ① cable: NO When using ② + ③ cable: YES | v2.00 | |
| Sony | A7R III | | | When using ① cable: 1. After connecting the cable, be sure to power on the Ronin-SC before the camera. Otherwise, the Ronin-SC will not recognize the camera. If the camera is not recognized, restart the camera or remove and reconnect the cable to the camera. 2. Optical zoom can be controlled through the Ronin-S Focus Wheel (only lenses with built-in power zoom, such as the Sony E PZ 18-105 mm F4 G OSS). If a non-Power Zoom lens is mounted, the Focus Wheel will control digital zoom. Digital zoom must be enabled in your camera's settings. 3. After connecting with a Sony camera using the ① cable, if you need to swap to a camera of other manufacturers then a gimbal reboot is required. | | v1.10 | |
| | A7R IV | ① Ronin-SC Multi-Camera Control Cable (Multi) (in the box) ② Ronin-SC Multi-Camera Control Cable (Type-C) (in the box) | When using ① cable: Capture photo Start/stop recording video Zoom control (digital or optical) Trigger auto focus When using ② cables: Start/stop recording video Pull focus electronically Trigger auto focus | When using ② cables: 1. Set the camera to MF mode. 2. Select "Network" and then turn off "Ctrl w/Smartphone". 3. Enable PC remote in the camera settings. 4. Optical Image Stabilization of the camera will be disabled when using MCC-C cable, but OIS of the lens will not be affected. 5. When using the focus control electronically, if the lens has AF/MF modes, set it to AF mode, otherwise the electronic focus control function cannot be used. Note: When using the ② cable, the camera may not be able to use playback. In this case, put the gimbal in sleep mode. | When using ① cable: NO When using ② cable: YES | v1.00 | |
| | A7 III | | | When using ② cables: 1. Set the camera to MF mode. 2. Select "Network" and then turn off "Ctrl w/Smartphone". 3. Enable PC remote in the camera settings. 4. Optical Image Stabilization of the camera will be disabled when using MCC-C cable, but OIS of the lens will not be affected. 5. When using the focus control electronically, if the lens has AF/MF modes, set it to AF mode, otherwise the electronic focus control function cannot be used. Note: When using the ② cable, the camera may not be able to use playback. In this case, put the gimbal in sleep mode. | | v1.01 | |
| | A7R II | | | | | v4.00 | |
| | A7S II | | | | | v3.00 | |
| | A7 II | | | | | v4.00 | |
| | A7S | | | | | v3.20 | |
| | A7 | | | | | v3.20 | |
| | A6600 | | | | | / | |
| | A6500 | | | | | v1.05 | |
| | A6300 | ① Ronin-SC Multi-Camera Control Cable (Multi) (in the box) | Capture photo Start/stop recording video Zoom control (digital or optical) Trigger auto focus | | 1. After connecting the cable, be sure to power on the Ronin-SC before the camera. Otherwise, the Ronin-SC does not recognize the camera. If the camera is not recognized, restart the camera or remove and reconnect the cable to the camera. 2. Optical zoom can be controlled through the Ronin-SC Focus Wheel (only lenses with built-in power zoom, such as the Sony E PZ 18-105 mm F4 G OSS). If a non-Power Zoom lens is mounted, the Focus Wheel will control digital zoom. Digital zoom must be enabled in your camera's settings. 3. After connecting with a Sony camera using the ① cable, if you need to swap to a camera of another brand then a gimbal reboot is required. | NO | v1.10 |
| | A6100 | | | | | / | |
| | A6000 | | | | | v3.20 | |
| | Rx100 VII | | | | | / | |
| | Rx100 VI | | | | | / | |
| | Rx100 V | | | | | / | |
| Rx10 IV | | | | | / | | |
| Rx10 III | | | | | / | | |
| Nikon | Z6 | ① Ronin-SC Multi-Camera Control Cable (Type-C) (in the box) | | | | v1.00 | |
| | Z7 | | | | | v1.01 | |
| | Z50 | ① Ronin-SC Multi-Camera Control Cable (Type-C) (in the box) + ① Ronin-SC Multi-Camera Control Adapter (Type-C to Micro USB) (in the box) | Start/stop recording video Capture photo Pull focus electronically Trigger auto focus | 1. To pull focus with Ronin-SC, set the lens focus mode to A, and make sure the camera focus mode is set to AF-S/AF-C. 2. Ensure live view on camera stays on when used with Ronin-SC. 3. Peaking highlights can only be displayed in MF mode. To use focus pull on Ronin-SC, the camera must be set to AF mode. In that case, peaking highlights cannot be displayed. | Camera powered on state: it will not power the camera Camera powered off state: using EN-EL15b battery, it will power the camera | v1.00 | |
| | D810 | | Due to the limit of D810 camera software, users can only take photos and record videos when the camera screen is blank. | The camera screen is blank after connecting the camera control cable. The monitor screen is also blank when connecting the HDMI cable. | / | v1.12 | |
| Canon | EOS R | | | 1. Due to various lens focus control mechanisms, when using the Ronin-SC to pull focus, you may need to set camera focus mode to AF. 2. When switched to Photo mode, the camera won't respond to video-capturing commands; when switched to video mode, the camera won't respond to photo-capturing commands. 3. Using adapter with EF lenses will increase the latency of focus. | | v1.0.0 | |
| | EOS RP | ① Ronin-SC Multi-Camera Control Cable (Type-C) (in the box) | | | | v1.1.0 | |
| | EOS M6 Mark II | | | / | | v1.0.0 | |
| | 90D | ① Ronin-SC Multi-Camera Control Cable (Type-C) (in the box) + ① Ronin-SC Multi-Camera Control Adapter (Type-C to Micro USB) (in the box) | Start/stop recording video Capture photo Pull focus electronically Trigger auto focus | 1. The focus speed should be set to lower than 10 when using the focus pull. 2. When switched to Photo mode, the camera won't respond to video-capturing commands; when switched to video mode, the camera won't respond to photo-capturing commands. | NO | v1.0.0 | |
| | EOS M50 | ① Ronin-SC Multi-Camera Control Cable (Type-C) (in the box) + ① Ronin-SC Multi-Camera Control Adapter (Type-C to Micro USB) (in the box) | | 1. When using the Camera Control button's auto focus, make sure the camera focus mode is set to AF | | v1.0.2 | |
| | G7 X Mark III | ① Ronin-SC Multi-Camera Control Cable (Type-C) (in the box) | Start/stop recording video Capture photo Trigger auto focus | The tilt axis of the gimbal cannot be balanced. It is recommended to perform auto tune for better use. | | v1.2.0 | |
| Panasonic | GH5 | ① Ronin-SC Multi-Camera Control Cable (Type-C) (in the box) | | | | v2.2 | |
| | GH5S | | | | | v1.1 | |
| | G9 | ① Ronin-SC Multi-Camera Control Cable (Type-C) (in the box) + ② Ronin-SC Multi-Camera Control Adapter (Type-C to Micro USB) (in the box) | Start/stop recording video Capture photo Pull focus electronically Trigger auto focus | 1. Choose PC (Tether) mode upon connection. 2. To pull focus with Ronin-S, the focus mode toggle on the camera should be set to MF. 3. To trigger camera's auto focus, half press the Camera Control button on the gimbal and ensure the camera's focus mode is set to AFS/AFF/AFC. | YES | v1.2 | |
| | GH3 | | | | | v1.1 | |
| | G95 | ① Ronin-SC RSS Control Cable for Panasonic (RSS-P) (optional) | Start/stop recording video Capture photo Trigger auto focus | Due to the limited space of the Ronin-SC equipped with a camera and lens, there are restrictions on the size and weight of the mounted lens. Please choose according to the actual situation. | NO | v1.1 | |
| | GH4 | | | | | v2.6 | |
| FUJIFILM | X-H1 | ① Ronin-SC Multi-Camera Control Cable (Type-C) (in the box) + ② Ronin-SC Multi-Camera Control Adapter (Type-C to Micro USB) (in the box) | When using ① + ② cable: Capture photo Trigger auto focus When using ③ cable: Start/stop recording video Capture photo Trigger auto focus | When using ① + ② cable: 1. Set PC connection mode to "USB Auto Mode." 2. The camera buttons' functions are not supported during the connection. To use the camera buttons' functions, make sure the gimbal is in sleep mode. | When using ① + ② cable: YES When using ③ cable: NO | v2.01 | |
| | X-T2 | ③ Ronin-SC RSS Control Cable for FUJIFILM (optional) | | | | v4.30 | |
| | X-T3 | ① Ronin-SC Multi-Camera Control Cable (Type-C) (in the box) ② Ronin-SC RSS Control Cable for FUJIFILM (optional) | When using ① cable: Capture photo Trigger auto focus Pull focus electronically Start/stop recording video When using ② cable: Start/stop recording video Capture photo Trigger auto focus | When using ① cable: 1. Set PC connection mode to "USB Auto Mode." 2. The camera buttons' functions are not supported during the connection. To use the camera buttons' functions, make sure the gimbal is in sleep mode. 3. Note that the camera is unable to auto focus in video recording mode. | When using ① cable: YES When using ② cable: NO | v3.10 | |
| | X-T4 | | | | | v1.00 | |
| | X-T20 | | | | | v2.01 | |
| | X-T30 | ① Ronin-SC RSS Control Cable for FUJIFILM (optional) | Start/stop recording video Capture photo Trigger auto focus | Requires camera settings: MOVIE SETTING->MIC/REMOTE RELEASE->REMOTE. | No | v1.00 | |
| | X100V | | | | | v1.10 | |
| | X-E3 | | | | | v1.22 | |

Notes:

- The current camera firmware version that was used during these compatibility tests.
- The form will be continuously updated as more compatibility is added and is subject to change without notice.
- The information in the lens compatibility table will be continuously updated after testing is completed. Other lenses not listed in the table may be compatible if mechanical balance can be achieved on the Ronin-SC.
- In order to reduce the overall weight, the Ronin-SC's balance dimensions are limited, so some cameras can not enter flashlight mode after balancing. If listed to support flashlight mode, the test is carried out in a state where only the camera is installed (the viewfinder's eyecup may need to be removed). This list is for reference only, please refer to the actual use.
- Some cameras may not be able to shoot when proper focus has not been achieved due to too focus speed or in a complex environments such as low light situations. If there's an issue with the shutter or rec button not responding properly in these situations, manual focus mode is recommended.
- When using intelligent functions such as timelapse, it is recommended to turn off the camera's auto review (Sony) or image confirmation (Canon) to reduce system latency.
- Due to manufacturing changes from various camera manufactures, the weight range calculated in the table is for reference only. Total weight calculation (camera + lens + phone holder + iPhone XS + focus motor).
- An iPhone6 was used as the model for illustration of the phone holder installation. Due to the variety of mobile phones, the installation position may be different. The installation support status in this table is for reference only. Please refer to the actual installation.
- Some cameras will draw power from the gimbal due to the limitations of the USB protocol which will have different effects on the battery life of Ronin-SC.
- The gimbal's range of motion might be restricted if the listed lens doesn't support flashlight mode after balancing.
- The Ronin-S/SC Focus Wheel is required to use focus pull. If the Ronin-S/SC Focus Wheel is not included in your purchase, purchase it separately.



Ronin-SC Lens Compatibility List

| | | Adaptation status | | | | | Mechanical adjustment of four combined installations | | | | | | | |
|-----------------------------------|--|---|-----------------------------|------------------------------|--|------------------------------------|--|--------------|---------------------|---|---|---|---|---|
| Brand | Model | Lens | Total weight range (lowest) | Total weight range (highest) | Camera Riser Required (with camera only) | Flashlight mode (with camera only) | Camera | Camera+Phone | Focus Motor+ Camera | Focus Motor+ Camera+Phone(1) | Remarks | Reference link | | |
| SONY | A7R III A7 III A9 A7S II A7R II A7 II | E 10-18mm F4 OSS | 1233 | 1265 | NO | YES | YES | YES | YES | YES | | https://cdn.djivideos.com/watch/6b796534-b58c-49a3-a348-77a754d1f147autoplay=false&poster= | | |
| | | FE 12-24mm F4 G | 1573 | 1605 | YES | YES | YES | YES | YES | YES | | https://cdn.djivideos.com/watch/b6c25bfb-bcd5-480a-a15f-2a6bc5ee7137autoplay=false&poster= | | |
| | | FE 16-35mm F2.8 GM | 1688 | 1720 | YES | NO | YES | YES | YES | YES | YES | Use of counterweights are needed to offset positioning enabling the use of flashlight mode (camera only). It is recommended to use Ronin-S/SC L-Bracket Plate with Counterweight for best performance. (https://store.dji.com/product/ronin-s-l-bracket-plate-with-counterweight) | https://cdn.djivideos.com/watch/01e3ed10-0581-41d6-852a-2e2329163b42?autoplay=false&poster= | |
| | | Vario-Tessar FE 24-70mm F4 ZA OSS | 1434 | 1466 | NO | YES | YES | YES | YES | YES | YES | | https://cdn.djivideos.com/watch/ea2031bf-6ae3-4158-a952-9d782985bd96?autoplay=false&poster= | |
| | | FE 24-70 F2.8 GM | 1894 | 1926 | YES | NO | YES | NO | NO | NO | NO | Use of counterweights are needed to offset positioning enabling the use of flashlight mode (camera only). It is recommended to use Ronin-S/SC L-Bracket Plate with Counterweight for best performance. (https://store.dji.com/product/ronin-s-l-bracket-plate-with-counterweight) | https://cdn.djivideos.com/watch/e27310ab-3bb2-42fd-8722-0186f7515814?autoplay=false&poster= | |
| | | Zeiss E 16-70 F4 OSS | 1316 | 1348 | NO | YES | YES | YES | YES | YES | YES | | https://cdn.djivideos.com/watch/c73c7129-23ed-4596-a829-a95cddc375c5?autoplay=false&poster= | |
| | | E PZ 18-105mm F4 G OSS | 1435 | 1467 | NO | YES | YES | YES | YES | YES | YES | | https://cdn.djivideos.com/watch/823d0e94-9711-4e12-8928-87448e71dd47?autoplay=false&poster= | |
| | | E PZ 18-200mm F3.5-6.3 OSS LE | 1657 | 1689 | / | NO | NO | NO | NO | NO | NO | | / | |
| | | FE 28mm F2 | 1208 | 1240 | NO | YES | YES | YES | YES | YES | YES | | https://cdn.djivideos.com/watch/423fee14-ada8-4612-be15-fe0c10fb96c4?autoplay=false&poster= | |
| | | Zeiss FE 35mm F2.8 ZA | 1128 | 1160 | NO | YES | YES | YES | YES | YES | YES | | https://cdn.djivideos.com/watch/19bd5814-afc2-4fb8-9b9f-cba469abbb99?autoplay=false&poster= | |
| | | Sigma 30mm f/1.4 DC DN | 1273 | 1305 | NO | YES | YES | YES | YES | YES | YES | | https://cdn.djivideos.com/watch/97734220-ae6f-4b2f-91b5-4d9981194659?autoplay=false&poster= | |
| | | Sigma 35mm f1.4 DG HSM Art | 1638 | 1670 | YES | NO | YES | YES | YES | YES | YES | Use of counterweights are needed to offset positioning enabling the use of flashlight mode (camera only). It is recommended to use Ronin-S/SC L-Bracket Plate with Counterweight for best performance. (https://store.dji.com/product/ronin-s-l-bracket-plate-with-counterweight) | https://cdn.djivideos.com/watch/01a12d7d-4d66-48c0-b41b-024db95b773?autoplay=false&poster= | |
| | | FE 55mm F1.8 | 1289 | 1321 | NO | YES | YES | YES | YES | YES | YES | | https://cdn.djivideos.com/watch/3f43d54c-f196-46e6-a893-5f527995cb43?autoplay=false&poster= | |
| | | FE 50mm F2.8 MACRO | 1244 | 1276 | NO | YES | YES | YES | YES | YES | YES | | https://cdn.djivideos.com/watch/ad29e04f-fe30-4965-aa8f-26121397de05?autoplay=false&poster= | |
| | | FE 4/24-105 G OSS | 1671 | 1703 | YES | NO | YES | YES | YES | YES | YES | Use of counterweights are needed to offset positioning enabling the use of flashlight mode (camera only). It is recommended to use Ronin-S/SC L-Bracket Plate with Counterweight for best performance. (https://store.dji.com/product/ronin-s-l-bracket-plate-with-counterweight) | https://cdn.djivideos.com/watch/69b2384d-528c-41d6-b786-4d325b6426e6?autoplay=false&poster= | |
| | | E 3.5-5.6/PZ 16-50 OSS | 1158 | 1190 | NO | YES | YES | YES | YES | YES | YES | | https://cdn.djivideos.com/watch/96a55a81-01e5-4925-ab6d-160ade56cdf?autoplay=false&poster= | |
| | | FE 24mm F1.4 GM | 1453 | 1485 | NO | YES | YES | YES | YES | YES | YES | | https://www.djivideos.com/watch/e0b4c0c0-162e-4c41-8c08-60a3a5450caa?autoplay=false&poster= | |
| | | FE 85mm F1.4 GM | 1908 | 1940 | YES | NO | YES | YES | YES | YES | YES | Use of counterweights are needed to offset positioning enabling the use of flashlight mode (camera only). It is recommended to use Ronin-S/SC L-Bracket Plate with Counterweight for best performance. (https://store.dji.com/product/ronin-s-l-bracket-plate-with-counterweight) | https://cdn.djivideos.com/watch/b94813d1-b7a2-4eca-bb1f-5bd2879937?autoplay=false&poster= | |
| | | A6500 A6400 A6300 | A6500 A6400 A6300 | E 10-18mm F4 OSS | 1036 | 1087 | YES | YES | YES | YES | YES | YES | | https://cdn.djivideos.com/watch/5c7d80a8-995e-43b8-bd60-8a2aa7b8353?autoplay=false&poster= |
| | | | | FE 12-24mm F4 G | 1376 | 1427 | YES | YES | YES | YES | YES | YES | | https://cdn.djivideos.com/watch/143992c-7828-41a9-8d1c-3f06e713d8ff?autoplay=false&poster= |
| FE 16-35mm F2.8 GM | 1491 | | | 1542 | YES | NO | YES | YES | YES | YES | YES | Use of counterweights are needed to offset positioning enabling the use of flashlight mode (camera only). It is recommended to use Ronin-S/SC L-Bracket Plate with Counterweight for best performance. (https://store.dji.com/product/ronin-s-l-bracket-plate-with-counterweight) | https://cdn.djivideos.com/watch/6f7953dc-ee3d-4c33-8626-2244c2710b17?autoplay=false&poster= | |
| Vario-Tessar FE 24-70mm F4 ZA OSS | 1237 | | | 1288 | YES | YES | YES | YES | YES | YES | YES | | https://cdn.djivideos.com/watch/660adaee-559a-48cd-82d3-1de605c57e2?autoplay=false&poster= | |
| FE 24-70 F2.8 GM | 1697 | | | 1748 | / | NO | NO | NO | NO | NO | NO | | / | |
| Zeiss E 16-70 F4 OSS | 1119 | | | 1170 | YES | YES | YES | YES | YES | YES | YES | | https://cdn.djivideos.com/watch/916a0208-85e7-47dc-a599-734817602acc?autoplay=false&poster= | |
| E PZ 18-105mm F4 G OSS | 1238 | | | 1289 | YES | YES | YES | YES | YES | YES | YES | | https://cdn.djivideos.com/watch/e6e2e03a-3a47-42f4-b27e-ea3902a35cd?autoplay=false&poster= | |
| E PZ 18-200mm F3.5-6.3 OSS LE | 1460 | | | 1511 | / | NO | NO | NO | NO | NO | NO | | / | |
| FE 28mm F2 | 1011 | | | 1062 | YES | YES | YES | YES | YES | YES | YES | | https://cdn.djivideos.com/watch/c756d5c8-8d57-4b6a-98c8-4cf0e2689b59?autoplay=false&poster= | |
| Zeiss FE 35mm F2.8 ZA | 931 | | | 982 | YES | YES | YES | YES | YES | YES | YES | | https://cdn.djivideos.com/watch/9f7565f-cbe1-4277-93c3-37614d686c713?autoplay=false&poster= | |
| Sigma 30mm f/1.4 DC DN | 1076 | | | 1127 | YES | YES | YES | YES | YES | YES | YES | | https://cdn.djivideos.com/watch/18577d5d-bae3-431f-8cfe-93d1aa0daac7?autoplay=false&poster= | |
| Sigma 35mm f1.4 DG HSM Art | 1441 | | | 1492 | YES | NO | YES | YES | YES | YES | YES | Use of counterweights are needed to offset positioning enabling the use of flashlight mode (camera only). It is recommended to use Ronin-S/SC L-Bracket Plate with Counterweight for best performance. (https://store.dji.com/product/ronin-s-l-bracket-plate-with-counterweight) | https://cdn.djivideos.com/watch/d77615bc-fa06-495b-9f7e-5554042f8667?autoplay=false&poster= | |
| FE 55mm F1.8 | 1092 | | | 1143 | YES | YES | YES | YES | YES | YES | YES | | https://cdn.djivideos.com/watch/1662500b-aaa0-4c64-92dc-75435e2278f?autoplay=false&poster= | |
| FE 50mm F2.8 MACRO | 1047 | | | 1098 | YES | YES | YES | YES | YES | YES | YES | | https://cdn.djivideos.com/watch/94a1b71e-1616-4f96-a91b-1a1ae862e7d7?autoplay=false&poster= | |
| FE 4/24-105 G OSS | 1474 | | | 1525 | YES | NO | YES | YES | YES | YES | YES | Use of counterweights are needed to offset positioning enabling the use of flashlight mode (camera only). It is recommended to use Ronin-S/SC L-Bracket Plate with Counterweight for best performance. (https://store.dji.com/product/ronin-s-l-bracket-plate-with-counterweight) | https://cdn.djivideos.com/watch/132f546-be35-471a-bdcb-a513e931fa2?autoplay=false&poster= | |
| E 3.5-5.6/PZ 16-50 OSS | 961 | | | 1012 | YES | YES | YES | YES | YES | YES | YES | | https://cdn.djivideos.com/watch/4fb34c3a-1a48-4c45-8f66-31419f77399d?autoplay=false&poster= | |
| FE 85mm F1.4 GM | 1711 | 1762 | YES | NO | YES | YES | YES | YES | YES | Use of counterweights are needed to offset positioning enabling the use of flashlight mode (camera only). It is recommended to use Ronin-S/SC L-Bracket Plate with Counterweight for best performance. (https://store.dji.com/product/ronin-s-l-bracket-plate-with-counterweight) | https://cdn.djivideos.com/watch/ea59cc3-81d0-4aba-bca3fc90c62ee?autoplay=false&poster= | | | |
| RX100 V | / | / | / | YES | YES | YES | YES | NO | NO | Use of Camera Cage is needed | https://cdn.djivideos.com/watch/6231fa4d-3564-4f6f-be00-08890c4098c?autoplay=false&poster= | | | |
| Panasonic | GH5S GH5 G9 | LEICA DG SUMMILUX 15mm f/1.7 ASPH | 1225 | 1292 | NO | YES | YES | YES | NO | NO | Due to lens and camera size limitations, it is currently not possible to install a focus motor | https://cdn.djivideos.com/watch/92a0b611-0d71-4c70-b652-28881a05609e?autoplay=false&poster= | | |
| | | LEICA DG SUMMILUX 25mm f/1.4 ASPH | 1235 | 1302 | NO | YES | YES | YES | YES | YES | | https://cdn.djivideos.com/watch/aa1c5374-8fc6-47ad-a5d2-9951e9d7b2?autoplay=false&poster= | | |
| | | LEICA DG MACRO 45mm f/2.8 OIS | 1335 | 1402 | NO | YES | YES | YES | YES | YES | | https://cdn.djivideos.com/watch/c598109c-a796-4913-a45a-80fcd72e68d1?autoplay=false&poster= | | |
| | | LEICA DG Vario-Elmarit 8-18mm f/2.8-4.0 ASPH | 1425 | 1492 | NO | YES | YES | YES | YES | YES | | https://cdn.djivideos.com/watch/0f036504-8d5b-442f-9760-0f7c6119839d?autoplay=false&poster= | | |
| | | LEICA DG Vario-Elmarit 12-60 f/2.8-4 Power OIS | 1430 | 1497 | NO | YES | YES | YES | YES | YES | YES | | https://cdn.djivideos.com/watch/cb1d728b-5a67-4eda-ba55-6190a8da5e?autoplay=false&poster= | |
| | | LUMIX G X Vario 12-35mm f/2.8 II ASPH POWER OIS | 1415 | 1482 | NO | YES | YES | YES | YES | YES | YES | | https://cdn.djivideos.com/watch/e1b133d3-58d4-4c79-9d09-8a547efd8078?autoplay=false&poster= | |
| | | LUMIX G 14-140mm f/4-5.8 OIS | 1375 | 1442 | NO | YES | YES | YES | YES | YES | YES | | / | |
| Nikon | Z6 Z7 | NIKKOR Z 35mm f/1.8 | 1497 | 1497 | NO | YES | YES | YES | YES | YES | | https://cdn.djivideos.com/watch/c1a71df7-e990-4ff3-ba25-3f824b860e2b?autoplay=false&poster= | | |
| | | NIKKOR Z 50mm f/1.8 S | 1542 | 1542 | YES | YES | YES | YES | YES | YES | | https://cdn.djivideos.com/watch/6033bb58-5b33-4b43-aea1-447e2d6174d7?autoplay=false&poster= | | |
| | | NIKKOR Z 24-70mm f/4 S | 1627 | 1627 | NO | YES | YES | YES | YES | YES | | https://cdn.djivideos.com/watch/271b705a-f21b-4127-b9ff-5edf587bc111?autoplay=false&poster= | | |
| | | NIKKOR Z 24-70mm f/2.8 S | 1932 | 1932 | Yes | No | Yes | Yes | Yes | Yes | | | | |
| | | NIKKOR Z DX 50-250mm f/4.5-6.3 VR | 1532 | 1532 | Yes | No | Yes | Yes | Yes | Yes | | | | |
| | | NIKKOR Z 14-30mm f/4 S | 1612 | 1612 | NO | YES | YES | YES | YES | YES | YES | | https://cdn.djivideos.com/watch/bb5ac3bc-cb70-4383-b63a-866e8ffed2f7?autoplay=false&poster= | |
| | | NIKKOR Z DX 50-250mm f/4.5-6.3 VR | 1307 | 1307 | Yes | No | Yes | Yes | Yes | Yes | Yes | | | |
| Z50 | NIKKOR Z DX 16-50mm f/3.5-6.3 VR | 1037 | 1037 | Yes | Yes | Yes | Yes | No | No | | | | | |
| Canon | EOS R | RF 35mm F1.8 MACRO IS STM | 1242 | 1417 | NO | YES | YES | YES | YES | YES | | https://cdn.djivideos.com/watch/b47ee6b5-5f65-4164-950b-0166d76061e7?autoplay=false&poster= | | |
| | | RF 50mm F1.2L USM | 1887 | 2062 | YES | NO | YES | YES | YES | YES | Use of counterweights are needed to offset positioning enabling the use of flashlight mode (camera only). It is recommended to use Ronin-S/SC L-Bracket Plate with Counterweight for best performance. (https://store.dji.com/product/ronin-s-l-bracket-plate-with-counterweight) | https://cdn.djivideos.com/watch/30cc89df-4e94-4f9d-bb0f-d0aaa576fd0e?autoplay=false&poster= | | |
| | | RF 28-70mm F2L USM | 2367 | 2542 | / | NO | NO | NO | NO | NO | | / | | |
| | | RF 24-105mm F4L IS USM | 1637 | 1812 | YES | NO | YES | YES | YES | YES | YES | Use of counterweights are needed to offset positioning enabling the use of flashlight mode (camera only). It is recommended to use Ronin-S/SC L-Bracket Plate with Counterweight for best performance. (https://store.dji.com/product/ronin-s-l-bracket-plate-with-counterweight) | / | |
| | | EOS 90D | EF-S 18-55mm f/4-5.6 IS STM | 215 | 1368 | NO | YES | YES | NO | YES | NO | | | |
| G7 X Mark III | 8.8-36.8mm 1:1.8-2.8 | 304 | 756 | YES | NO | NO | NO | NO | NO | | | | | |
| M50 | EF-M 15-45mm F3.5-6.3 IS | 972 | 972 | YES | YES | YES | NO | NO | NO | | / | | | |
| FUJIFILM | X-T2 X-T3 X-T4 | XF 16mm 1:1.4 R WR | 1334 | 1366 | NO | YES | YES | YES | YES | YES | | https://cdn.djivideos.com/watch/23669bf1-40b9-40f0-b08d-c1e825da8396?autoplay=false&poster= | | |
| | | XF 23mm 1:1.4 R | 1259 | 1291 | NO | YES | YES | YES | YES | YES | | https://cdn.djivideos.com/watch/0a245257-1433-4144-b99e-19ec4180178?autoplay=false&poster= | | |
| | | XF | | | | | | | | | | | | |